

DRAPER[®]

140mm

MAINS TESTER

10200

Read this manual in full before using this product and retain it for future use. Always use the latest version of the manual, available from drapertools.com/manuals

Specification

Stock No.	10200
Part No.	MT-140
Voltage testing range:	100–250V AC
Blade width:	3mm
Recommended temperature range:	-10 to +50°C (14–122°F)



WARNING! Risk of shock.

- Exercise caution when working with live electricity.
- **NEVER** use this product in wet environments or with wet hands.
- **NEVER** touch any exposed metal that is in contact with the live circuit.

Important: DO NOT attempt to test power supplies beyond the voltage rated for this device. **DO NOT** operate this product where explosive gases, vapours or dust may be present.

Important: DO NOT attempt to modify, open or dismantle this product. **DO NOT** use this product if it is damaged in any way.

Operation

Important: Test the product on a known live circuit before **EVERY** use to ensure that it is functioning correctly.

1. Insert the blade into the live (right) aperture of an outlet or touch the blade against a live circuit. Use a socket gate (not supplied) where necessary.
2. Place your thumb over the metal contact on the handle of the device.
3. The internal LED illuminates if a live voltage is detected. The light will not illuminate if the blade is inserted into a neutral aperture or the circuit is not live.

If you are in any doubt over the results of a test, consult a qualified electrician.



CAUTION! DO NOT use this product as a screwdriver as it may damage the tester.



At the end of its working life, dispose of the product responsibly and in line with local regulations.

DO NOT dispose of this product with domestic waste; most local authorities provide appropriate recycling facilities.

Symbols



Warning



WEEE – Waste Electrical & Electronic Equipment Do not dispose of this product with domestic waste



UK Conformity Assessed



European Conformity