# ZIRCON®

# PRODUCT INFO LEAK ALERT<sup>TM</sup> WATER DETECTOR ZN-WD100



BARCODE: DIMENSIONS: WEIGHT: BATTERY TYPE: LOW BATTERY: SOUND INTENSITY: OPERATING TEMP: STORAGE TEMP: HUMIDITY: SHOCK RESISTANCE:

#### 042186706741

35mm x 61mm x 109mm 69g (without battery) 9V alkaline (not included) Unit will beep to indicate 90 dB -7° to 41°C

-29° to 66°C

5 - 90% RH (non-condensing)

SHOCK RESISTANCE: From 1.8m drop on concreteWATER RESISTANCE: Splash proof, not waterproof. Floats on surface if battery is installed correctly.

# Electronic Water Detector

Prevent serious water damage with help from the Leak Alert<sup>™</sup> water detector. This self-contained battery-powered unit will sound a loud alarm the second it gets wet, alerting you to a potential water leak.

Place it anywhere the potential for flooding or leaking exists:

- Under sinks
- Near water heaters
- In basements
- Near dishwashers and refrigerators
- Under fish tanks
- Near plumbing and toilets

## **HOW DOES IT WORK?**

The Leak Alert<sup>™</sup> has two external metal strips with mild electrical current running through them. If both strips get wet, through a plumbing leak, flood, or surrounding moisture condensing on the surface, the electrical circuit will complete and the alarm will sound.

Make sure the Leak Alert<sup>™</sup> is placed on its back with the metal contacts touching the surface. You can test the unit by touching both strips with one finger, but be prepared for the loud alarm!

## **FEATURES**

- Loud alarm (90 dB) sounds with direct water contact
- Floats and signals for the life of the battery
- Fully automatic operation no wiring required
- Low battery indicator for optimum safety and performance



